

## TELEPHONE FEATURES

---

### CONFERENCE CALL WITH ITE-12+, 12S, 24, AND 30S

To add third through seventh parties:

- 1** Press **CONF**.
- 2** You should hear the dial tone.
- 3** The **CONF** lamp should be blinking.
- 4** The conference should be placed on hold.
- 5** Dial the phone number to be added to the conference.
- 6** Press **CONF**.
- 7** The party should be added to the conference.
- 8** The **CONF** lamp should be ON.

If busy, unanswered, or wrong number:

- 1** Press the switch hook.
- 2** Press the extension the conference is on.
- 3** You should hear the dial tone.
- 4** Press **CONF**.
- 5** The conference should be reactivated.
- 6** The **CONF** lamp should be ON.

To place a conference on hold:

- 1** Press **CONF**.
- 2** Hang up.
- 3** The **CONF** lamp should be blinking.

To reactivate a conference that has been put on hold:

- 1** Lift the handset and press the extension the conference is on.
- 2** Press **CONF**.
- 3** The conference should be reactivated.
- 4** The **CONF** lamp should be ON.